

April 2015

FDB390N15A

N-Channel PowerTrench[®] MOSFET 150 V, 27 A, 39 m Ω

Features


- $R_{DS(on)}$ = 33.5 m Ω (Typ.) @ V_{GS} = 10 V, I_D = 27 A
- · Fast Switching Speed
- Low Gate Charge, Q_G = 14.3 nC (Typ.)
- High Performance Trench Technology for Extremely Low $R_{DS(on)}$
- · High Power and Current Handling Capability
- RoHS Compliant


Description

This N-Channel MOSFET is produced using Fairchild Semiconductor's advanced PowerTrench[®] process that has been tailored to minimize the on-state resistance while maintaining superior switching performance.

Applications

- · Consumer Appliances
- · LED TV
- · Synchronous Rectification
- · Uninterruptible Power Supply
- · Micro Solar Inverter





Absolute Maximum Ratings T_C = 25°C unless otherwise noted.

Symbol		Parameter			
V _{DSS}	Drain to Source Voltage		150	V	
V _{GSS}	Cata to Course Valtage	- DC	±20	\/	
	Gate to Source Voltage	- AC (f > 1 Hz)	±30	V	
Desire Courses		- Continuous (T _C = 25°C,Silicon Limited)	27	^	
'D	Drain Current	- Continuous (T _C = 100°C,Silicon Limited)	19	_ A	
I _{DM}	Drain Current	- Pulsed (Note 1)	108	Α	
E _{AS}	Single Pulsed Avalanche Energy (Note 2)		78	mJ	
dv/dt	Peak Diode Recovery dv/dt	(Note 3)	6.0	V/ns	
D	Pawer Discination	$(T_C = 25^{\circ}C)$	75	W	
P_{D}	Power Dissipation	- Derate Above 25°C	0.5	W/°C	
T _J , T _{STG}	Operating and Storage Temperature Range		-55 to +175	°C	
T _L	Maximum Lead Temperature for	Maximum Lead Temperature for Soldering, 1/8" from Case for 5 Seconds.		οС	

Thermal Characteristics

Symbol	Parameter	FDB390N15A	Unit
$R_{\theta JC}$	Thermal Resistance, Junction to Case, Max.	2.0	
В	Thermal Resistance, Junction to Ambient (Minimum Pad of 2-oz Copper), Max.	62.5	°C/W
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient (1 in ² Pad of 2-oz Copper), Max.	40	

Package Marking and Ordering Information

Part Number	Top Mark	Package	Packing Method	Reel Size	Tape Width	Quantity
FDB390N15A	FDB390N15A	D ² -PAK	Tape and Reel	330 mm	24 mm	800 units

Electrical Characteristics $T_C = 25^{\circ}C$ unless otherwise noted.

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
Off Charac	cteristics					
BV _{DSS}	Drain to Source Breakdown Voltage	$I_D = 250 \mu A, V_{GS} = 0 V$	150	-	-	V
ΔBV _{DSS} / ΔT _J	Breakdown Voltage Temperature Coefficient	I_D = 250 μA, Referenced to 25°C	-	0.1	-	V/°C
1	Zero Gate Voltage Drain Current	V _{DS} = 120 V, V _{GS} = 0 V	-	-	1	
IDSS	Zero Gate voltage Drain Current	$V_{DS} = 120 \text{ V}, T_{C} = 150^{\circ}\text{C}$	-	-	500	μΑ
I _{GSS}	Gate to Body Leakage Current	V _{GS} = ±20 V, V _{DS} = 0 V	-	-	±100	nA

On Characteristics

V _{GS(th)}	Gate Threshold Voltage	$V_{GS} = V_{DS}, I_D = 250 \mu A$	2.0	-	4.0	V
R _{DS(on)}	Static Drain to Source On Resistance	V _{GS} = 10 V, I _D = 27 A	-	33.5	39.0	mΩ
9 _{FS}	Forward Transconductance	V _{DS} = 10 V, I _D = 27 A	-	33	-	S

Dynamic Characteristics

C _{iss}	Input Capacitance	V - 75 V V - 0 V	-	965	1285	pF
C _{oss}	Output Capacitance	V _{DS} = 75 V, V _{GS} = 0 V, f = 1 MHz		96	130	pF
C _{rss}	Reverse Transfer Capacitance			5.8	-	pF
C _{oss(er)}	Energy Related Output Capacitance	V _{DS} = 75 V, I _D = 27 A		169	-	pF
Q _{g(tot)}	Total Gate Charge at 10V		-	14.3	18.6	nC
Q_{gs}	Gate to Source Gate Charge	$V_{DS} = 75 \text{ V}, I_D = 27 \text{ A},$		5.0	-	nC
Q _{gs2}	Gate Charge Threshold to Plateau	V _{GS} = 10 V	-	2.0	-	nC
Q_{gd}	Gate to Drain "Miller" Charge	(Note 4)	-	3.5	-	nC
ESR	Equivalent Series Resistance (G-S)	f = 1 MHz	-	1.4	-	Ω

Switching Characteristics

t _{d(on)}	Turn-On Delay Time		- /	14	38	ns
t _r		$V_{DD} = 75 \text{ V}, I_{D} = 27 \text{ A},$	-/	10	30	ns
t _{d(off)}	Turn-Off Delay Time	V_{GS} = 10 V, R_{G} = 4.7 Ω	-	20	50	ns
t _f	Turn-Off Fall Time	(Note 4)	-	5	20	ns

Drain-Source Diode Characteristics

I _S	Maximum Continuous Drain to Source Diode Forward Current			-	27	Α
I _{SM}	Maximum Pulsed Drain to Source Diode Forward Current			-	108	Α
V_{SD}	Drain to Source Diode Forward Voltage V _{GS} = 0 V, I _{SD} = 27 A		-	- ,,,/	1.25	V
t _{rr}	Reverse Recovery Time	V _{GS} = 0 V, I _{SD} = 27 A, V _{DD} = 75 V,	-	63	-	ns
Q _{rr}	Reverse Recovery Time $V_{GS} = 0 \text{ V}, I_{SD} = 27 \text{ A}, V_{DD} = 75 \text{ V},$ Reverse Recovery Charge $dI_F/dt = 100 \text{ A}/\mu\text{s}$		-	131	-	nC

Notes

- ${\it 1. Repetitive\ rating: pulse-width\ limited\ by\ maximum\ junction\ temperature.}$
- 2. Starting T_J = 25°C, L = 3 mH, I_{SD} = 7.2 A.
- 3. I $_{SD} \le 27$ A, di/dt ≤ 200 A/µs, V $_{DD} \le BV _{DSS},$ starting T $_{J}$ = 25°C.
- 4. Essentially independent of operating temperature typical characteristics.

Typical Performance Characteristics

Figure 1. On-Region Characteristics




Figure 3. On-Resistance Variation vs.

Drain Current and Gate Voltage




Figure 5. Capacitance Characteristics




Figure 2. Transfer Characteristics




Figure 4. Body Diode Forward Voltage Variation vs. Source Current and Temperature





Figure 6. Gate Charge Characteristics



Typical Performance Characteristics (Continued)

Figure 7. Breakdown Voltage Variation vs. Temperature




Figure 9. Maximum Safe Operating Area




Figure 11. Eoss vs. Drain to Source Voltage




Figure 8. On-Resistance Variation vs. Temperature




Figure 10. Maximum Drain Current vs. Case Temperature






Figure 12. Unclamped Inductive Switching Capability



Typical Performance Characteristics (Continued)

Figure 13. Transient Thermal Response Curve






Figure 14. Gate Charge Test Circuit & Waveform




Figure 15. Resistive Switching Test Circuit & Waveforms




Figure 16. Unclamped Inductive Switching Test Circuit & Waveforms





Figure 17. Peak Diode Recovery dv/dt Test Circuit & Waveforms







TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

 $\begin{array}{lll} \mathsf{AccuPower^{\mathsf{TM}}} & \mathsf{F-PFS^{\mathsf{TM}}} \\ \mathsf{AttitudeEngine^{\mathsf{TM}}} & \mathsf{FRFET}^{\texttt{®}} \end{array}$

Awinda[®] Global Power Resource SM

AX-CAP®* GreenBridge™
BitSiC™ Green FPS™
Build it Now™ Green FPS™ e-Series™

Current Transfer Logic™ Making Small Speakers Sound Louder

DEUXPEED® and Better™

Dual Cool™ MegaBuck™

EcoSPARK® MICROCOUPLER™

EfficientMax™ MicroFET™

EfficientMax™ MicroFET™
ESBC™ MicroPak™
MicroPak™
MicroPak2™
Fairchild® MillerDrive™
MotionMax™
Fairchild Semiconductor®

Farchild Semiconductor

FACT Quiet Series™
FACT®

FastvCore™
FETBench™
FPS™

MotionGrid®
MTI®
MTX®
MVN®
FETBench™
MVN®
FPS™

OptoHiT™
OPTOLOGIC®

OPTOPLANAR®

Power Supply WebDesigner™ PowerTrench®

PowerXS™

Programmable Active Droop™ OFFT®

QS™ Quiet Series™ RapidConfigure™

TM TM

Saving our world, 1mW/W/kW at a time™

SignalWise™ SmartMax™ SMART START™

Solutions for Your Success™

SPM®
STEALTH™
SuperFET®
SuperSOT™-3
SuperSOT™-6
SuperSOT™-8
SupreMOS®
SyncFET™
Sync-Lock™

SYSTEM GENERAL®'
TinyBoost®
TinyBuck®
TinyCalc™
TinyLogic®
TINYOPTO™
TinyPower™
TinyPWM™
TinyPWM™
TranSiC™
TriFault Detect™
TRUECURRENT®**
uSerDes™

SerDes"
UHC[®]
Ultra FRFET™
UniFET™
VCX™
VisualMax™
VoltagePlus™
XS™
XS™
XS™

仙童®

* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. TO OBTAIN THE LATEST, MOST UP-TO-DATE DATASHEET AND PRODUCT INFORMATION, VISIT OUR WEBSITE AT http://www.fairchildsemi.com, FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

AUTHORIZED USE

Unless otherwise specified in this data sheet, this product is a standard commercial product and is not intended for use in applications that require extraordinary levels of quality and reliability. This product may not be used in the following applications, unless specifically approved in writing by a Fairchild officer: (1) automotive or other transportation, (2) military/aerospace, (3) any safety critical application – including life critical medical equipment – where the failure of the Fairchild product reasonably would be expected to result in personal injury, death or property damage. Customer's use of this product is subject to agreement of this Authorized Use policy. In the event of an unauthorized use of Fairchild's product, Fairchild accepts no liability in the event of product failure. In other respects, this product shall be subject to Fairchild's Worldwide Terms and Conditions of Sale, unless a separate agreement has been signed by both Parties.

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Terms of Use

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Definition of Terms		
Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

Rev. 177

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

FDB390N15A