

SEMICONDUCTOR®

# **KSE44H Series**

## **General Purpose Power Switching Applications**

- Low Collector-Emitter Saturation Voltage : V<sub>CE</sub>(sat) = 1V (Max.) @ 8A
- Fast Switching Speeds
- Complement to KSE45H



1.Base 2.Collector 3.Emitter

# **NPN Epitaxial Silicon Transistor**

## Absolute Maximum Ratings T<sub>C</sub>=25°C unless otherwise noted

Symbol	Parameter		Value	Units	
V <sub>CEO</sub>	Collector-Emitter Voltage	: KSE44H 1,2	30	V	
		: KSE44H 4,5	45	V	
		: KSE44H 7,8	60	V	
		: KSE44H 10,11	80	V	
V <sub>EBO</sub>	Emitter- Base Voltage		5	V	
I <sub>C</sub>	Collector Current (DC)		10	А	
I <sub>CP</sub>	*Collector Current (Pulse)		20	А	
	Collector Dissipation (T <sub>C</sub> =25°C)		50	W	
P <sub>C</sub> P <sub>C</sub>	Collector Dissipation (T <sub>a</sub> =25°C)		1.67	W	
TJ	Junction Temperature		150	°C	
T <sub>STG</sub>	Storage Temperature		- 55 ~ 150	°C	


## Electrical Characteristics T<sub>C</sub>=25°C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Тур.	Max.	Units
I <sub>CES</sub>	Collector Cut-off Current	$V_{CE}$ = Rated $V_{CEO}$ , $V_{EB}$ = 0			10	μΑ
I <sub>EBO</sub>	Emitter Cut-off Current	$V_{EB} = 5V, I_{C} = 0$			100	μΑ
h <sub>FE</sub>	*DC Current Gain : KSE44H 1,4,7,10 : KSE44H 2,5,8,11	$V_{CE} = 1V, I_C = 2A$	35 60			
V <sub>CE</sub> (sat)	*Collector-Emitter Saturation Voltage : KSE44H 1, 4, 7 10 : KSE44H 2, 5, 8,11	I <sub>C</sub> = 8A, I <sub>B</sub> = 0.8A I <sub>C</sub> = 8A, I <sub>B</sub> = 0.4A			1 1	V V
V <sub>BE</sub> (sat)	*Base-Emitter Saturation Voltage	$I_{\rm C} = 8$ A, $I_{\rm B} = 0.8$ A			1.5	V
f <sub>T</sub>	Current Gain Bandwidth Product	$V_{CE} = 10V, I_{C} = 0.5A$		50		MHz
f <sub>T</sub> C <sub>ob</sub>	Output Capacitance	V <sub>CB</sub> = 10V, f = 1MHz		130		pF
t <sub>ON</sub>	Turn ON Time	$V_{CC} = 20V, I_{C} = 5A$		300		ns
t <sub>STG</sub>	Storage Time	I <sub>B1</sub> = - I <sub>B2</sub> = 0.5A		500		ns
t <sub>F</sub>	Fall Time	1		140		ns


\* Pulse test: PW≤300µs, Duty cycle≤2%

**KSE44H Series** 

©2001 Fairchild Semiconductor Corporation



©2001 Fairchild Semiconductor Corporation



#### TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx<sup>TM</sup> Bottomless<sup>TM</sup> CoolFET<sup>TM</sup>  $CROSSVOLT^{TM}$ DenseTrench<sup>TM</sup> DOME<sup>TM</sup> EcoSPARK<sup>TM</sup>  $E^2CMOS^{TM}$ EnSigna<sup>TM</sup> FACT<sup>TM</sup> FACT Quiet Series<sup>TM</sup> FAST<sup>®</sup> FASTr<sup>™</sup> FRFET<sup>™</sup> GlobalOptoisolator<sup>™</sup> GTO<sup>™</sup> HiSeC<sup>™</sup> ISOPLANAR<sup>™</sup> LittleFET<sup>™</sup> MicroFET<sup>™</sup> MICROWIRE<sup>™</sup> OPTOLOGIC<sup>™</sup>

OPTOPLANAR™ PACMAN™ POP™ Power247™ PowerTrench<sup>®</sup> QFET™ QS™ QT Optoelectronics™ Quiet Series™ SLIENT SWITCHER<sup>®</sup> SMART START™ STAR\*POWER<sup>™</sup> Stealth<sup>™</sup> SuperSOT<sup>™</sup>-3 SuperSOT<sup>™</sup>-6 SuperSOT<sup>™</sup>-8 SyncFET<sup>™</sup> TruTranslation<sup>™</sup> TinyLogic<sup>™</sup> UHC<sup>™</sup> UltraFET<sup>®</sup> VCX<sup>™</sup>

STAR\*POWER is used under license

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.

2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

#### **PRODUCT STATUS DEFINITIONS**

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Fairchild Semiconductor: KSE44H11 KSE44H11TU