

# SB120 - SB1100

### **Features**

- 1.0 ampere operation at T<sub>A</sub> = 75°C with no thermal runaway.
- For use in low voltage, high frequency inverters free wheeling, and polarity protection applications.



# **Schottky Rectifiers**

### Absolute Maximum Ratings\* T<sub>A</sub> = 25°C unless otherwise noted

Symbol	Parameter	Value							Units
		120	130	140	150	160	180	1100	
$V_{RRM}$	Maximum Repetitive Reverse Voltage		30	40	50	60	80	100	V
I <sub>F(AV)</sub>	Average Rectified Forward Current .375 " lead length @ $T_A = 75$ °C	1.0				Α			
I <sub>FSM</sub>	Non-repetitive Peak Forward Surge Current 8.3 ms Single Half-Sine-Wave		30					Α	
T <sub>stg</sub>	Storage Temperature Range		-65 to +125						°C
T <sub>J</sub>	Operating Junction Temperature		-65 to +125						°C

<sup>\*</sup>These ratings are limiting values above which the serviceability of any semiconductor device may be impaired.

### **Thermal Characteristics**

Symbol	Parameter	Value	Units
P <sub>D</sub>	Power Dissipation	1.25	W
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient	80	°C/W


# 

Symbol	Parameter		Device						
			130	140	150	160	180	1100	
V <sub>F</sub>	Forward Voltage @ 1.0 A		500		700		850		mV
I <sub>R</sub>	Reverse Current @ rated $V_R$ $T_A = 25^{\circ}C$ $T_A = 100^{\circ}C$		0.5 10						mA mA
Im	Maximum Full Load Reverse Current, Full Cycle $T_A = 75$ °C		30					mA	
Ст	Total Capacitance V <sub>R</sub> = 4.0 V, f = 1.0 MHz		110						pF

### **Schottky Rectifier**

(continued)

### **Typical Characteristics**



**Figure 1. Forward Current Derating Curve** 




Figure 2. Forward Voltage Characteristics




Figure 3. Non-Repetitive Surge Current




Figure 4. Total Capacitance

#### **TRADEMARKS**

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

SMART START™  $VCX^{TM}$ FAST ® OPTOLOGIC™ STAR\*POWER™ FASTr™ Bottomless™ OPTOPLANAR™ Stealth™ CoolFET™ FRFET™ PACMAN™ SuperSOT™-3 CROSSVOLT™ GlobalOptoisolator™ POP™ SuperSOT™-6 DenseTrench™ GTO™ Power247™  $HiSeC^{TM}$ SuperSOT™-8  $Power Trench^{\, @}$ DOME™ SyncFET™ EcoSPARK™ ISOPLANAR™ QFET™ TinyLogic™ E<sup>2</sup>CMOS<sup>TM</sup> LittleFET™  $OS^{TM}$ 

QT Optoelectronics™

MicroFET™

STAR\*POWER is used under license

#### DISCLAIMER

EnSigna™

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the

2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

TruTranslation™

### PRODUCT STATUS DEFINITIONS

### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary First Production		This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

Rev. H4

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Fairchild Semiconductor:

SB140 SB140F056 SB140\_F056