



2 CHANNEL LOW CAPACITANCE TVS DIODE ARRAY

Features


- IEC 61000-4-2 (ESD): Air ±15kV, Contact ±8kV
- 2 Channels of ESD Protection
- Low Channel Input Capacitance of 0.85pF Typical
- Typically Used at High Speed Ports such as USB 2.0, IEEE1394, Serial ATA, DVI, HDMI, PCI
- Totally Lead-Free & Fully RoHS Compliant (Notes 1 & 2)
- Halogen and Antimony Free. "Green" Device (Note 3)
- Qualified to AEC-Q101 Standards for High Reliability

Mechanical Data


- Case: SOT25
- Case Material: Molded Plastic, "Green" Molding Compound.
 UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020
- Terminals: Matte Tin Finish annealed over Copper leadframe (Lead Free Plating). Solderable per MIL-STD-202, Method 208 @3
- Weight: 0.016 grams (approximate)











Device Schematic


Ordering Information (Note 4)

Part Number	Case	Packaging
D1213A-02SM-7	SOT25	3000/Tape & Reel

Notes

- $1.\ No\ purposely\ added\ lead.\ Fully\ EU\ Directive\ 2002/95/EC\ (RoHS)\ \&\ 2011/65/EU\ (RoHS\ 2)\ compliant.$
- 2. See http://www.diodes.com for more information about Diodes Incorporated's definitions of Halogen- and Antimony-free, "Green" and Lead-free.
- 3. Halogen- and Antimony-free "Green" products are defined as those which contain <900ppm bromine, <900ppm chlorine (<1500ppm total Br + Cl) and <1000ppm antimony compounds.
- 4. For packaging details, go to our website at http://www.diodes.com.

Marking Information



TV3 = Product Type Marking Code YM = Date Code Marking Y = Year (ex: Z = 2012) M = Month (ex: 9 = September)

Date Code Key

Year	201	1	2012		2013	20)14	2015		2016		2017
Code	Υ		Z		Α		В	С		D		Е
Month	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Code	1	2	3	4	5	6	7	8	9	0	N	D



Maximum Ratings (@ $T_A = +25^{\circ}C$, unless otherwise specified.)

Characteristic	Symbol	Value	Unit	Conditions
Operating Supply Voltage	V _P - V _N	6.0	V	_
DC Voltage at any Channel Input	_	$(V_N - 0.5)$ to $(V_P + 0.5)$	V	_
Peak Pulse Current	I _{PP}	5	Α	8/20μs, Per Figure 3
ESD Protection – Contact Discharge	V _{ESD_Contact}	±8	kV	Standard IEC 61000-4-2
ESD Protection – Air Discharge	V_{ESD_Air}	±15	kV	Standard IEC 61000-4-2

Thermal Characteristics

Characteristic	Symbol	Value	Unit
Power Dissipation (Note 5)	P_{D}	400	mW
Thermal Resistance, Junction to Ambient (Note 5)	$R_{ hetaJA}$	310	°C/W
Operating and Storage Temperature Range	T _J , T _{STG}	-65 to +150	°C

Electrical Characteristics (@T_A = +25°C, unless otherwise specified.)

Characteristic	Symbol	Min	Тур	Max	Unit	Test Conditions
Operating Supply Voltage	V _P	_	3.3	5.5	V	_
Operating Supply Current (Note 6)	IР	_	_	8.0	μΑ	$(V_P - V_N) = 3.3V$
Channel Leakage Current (Note 6)	I _R	_	±0.1	±1.0	μΑ	$V_P = 5V, V_N = 0V$
Reverse breakdown voltage	V_{BR}	6.0	_	_	V	$I_R = 1 \text{mA}$
Clamping Voltage, Positive Transients	V _{CL1}	_	10.0	_	V	$I_{PP} = 1A, t_p = 8/20 \mu s$
Clamping Voltage, Negative Transients	V _{CL2}	_	-1.7	_	V	$I_{PP} = -1A, t_p = 8/20 \mu s$
Forward Voltage for Top Diode	V_{FD1}	0.60	0.80	0.95	V	$I_F = 8mA$, CH1 to V_P or CH2 to V_P
Forward Voltage for Bottom Diode	V_{FD2}	0.60	0.80	0.95	V	$I_F = 8mA$, V_N to CH1 or V_N to CH2
Dynamic Resistance	R _{DYN}	_	0.9	_	Ω	$I_{PP} = 1A, t_p = 8/20 \mu s$
Channel Input Capacitance	Ст	_	0.85	1.2	pF	$V_{IN} = 1.65V, V_P = 3.3V,$ $V_N = 0V, f = 1MHz$

Notes:

- 5. Device mounted on FR-4 PCB pad layout (2oz copper) as shown on Diodes, Inc. suggested pad layout AP02001, which can be found on our website at
- http://www.diodes.com.
 6. Short duration pulse test used to minimize self-heating effect.
 7. Measured from CH1 to Vn or CH2 to Vn.
- 8. Measured from $\ensuremath{V_P}$ to $\ensuremath{V_N}$.
- 9. For information on the impact of Diodes' USB 2.0 compatible ESD protectors on signal integrity including eye diagram plots, please refer to AN77 at the following URL: http://www.diodes.com/destools/appnote_dnote.html.










Figure 1 Power Dissipation vs. Ambient Temperature



t, TIME (μ s) Figure 3 Pulse Waveform











Figure 6 Typical Total Capacitance vs. Reverse Voltage



Package Outline Dimensions


Please see AP02002 at http://www.diodes.com/datasheets/ap02002.pdf for latest version.



	SOT25							
Dim	Min	Max	Тур					
Α	0.35	0.50	0.38					
В	1.50	1.70	1.60					
С	2.70	3.00	2.80					
D	_		0.95					
Н	2.90	3.10	3.00					
J	0.013	0.10	0.05					
K	1.00	1.30	1.10					
L	0.35	0.55	0.40					
M	0.10	0.20	0.15					
N	0.70	0.80	0.75					
α	0°	8°	_					
All Dimensions in mm								

Suggested Pad Layout

Please see AP02001 at http://www.diodes.com/datasheets/ap02001.pdf for the latest version.



Dimensions	Value (in mm)
Z	3.20
G	1.60
Х	0.55
Y	0.80
C1	2.40
C2	0.95



IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel. Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
 - 1. are intended to implant into the body, or
 - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2012, Diodes Incorporated

www.diodes.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Diodes Inc.: