

Is Now Part of



# **ON Semiconductor**®

To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor dates sheds, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor dates sheds and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use on similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor and its officers, employees, subsidiaries, affliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out or i, directly or indirectly, any lay bed ON Semiconductor and its officers, employees, ween if such claim alleges that ON Semiconductor was negligent regarding the d



# FJP1943 PNP Epitaxial Silicon Transistor

### Applications

- High-Fidelity Audio Output Amplifier
- General Purpose Power Amplifier

#### Features

- High Current Capability: I<sub>C</sub> = -15A.
- High Power Dissipation : 80watts.
- High Frequency : 30MHz.
- High Voltage : V<sub>CEO</sub>= -230V
- Wide S.O.A for reliable operation.
- Excellent Gain Linearity for low THD.
- Complement to FJP5200

. .

T<sub>J</sub>, T<sub>STG</sub>

- Full thermal and electrical Spice models are available.
  - Same transistor is also available in:
  - -- TO264 package, 2SA1943/FJL4215 : 150 watts
  - -- TO3P package, 2SA1962/FJA4213 : 130 watts
  - -- TO220F package, FJPF1943 : 50 watts

# 1 TO-220

1.Base 2.Collector 3.Emitter

- 50 ~ +150

Absolute Maximum Ratings <sup>*</sup> $T_a = 25^{\circ}C$ unless otherwise noted				
Symbol	Parameter	Ratings	Units V	
BV <sub>CBO</sub>	Collector-Base Voltage	-230		
BV <sub>CEO</sub>	Collector-Emitter Voltage	-230	V	
BV <sub>EBO</sub>	Emitter-Base Voltage	-5	V	
I <sub>C</sub>	Collector Current	-15	А	
I <sub>B</sub>	Base Current	-1.5	А	
P <sub>D</sub>	Total Device Dissipation(T <sub>C</sub> =25°C) Derate above 25°C	80 0.64	W W/°C	

\* These ratings are limiting values above which the serviceability of any semiconductor device may be impaired.

### $\label{eq:thermal} Thermal \ Characteristics^* \ \ T_a=25^\circ C \ \text{unless otherwise noted}$

Junction and Storage Temperature

Symbol	Parameter	Ratings	Units	
$R_{ extsf{ heta}JC}$	Thermal Resistance, Junction to Case	1.25	°C/W	
+ Davids manufacture and size				

Device mounted on minimum pad size

#### h<sub>FE</sub> Classification

Classification	R	0
h <sub>FE1</sub>	55 ~ 110 80 ~ 160	

November 2008


°C

Symbol	Parameter	Test Condition	Min.	Тур.	Max.	Units
BV <sub>CBO</sub>	Collector-Base Breakdown Voltage	I <sub>C</sub> =-5mA, I <sub>E</sub> =0	-230			V
BV <sub>CEO</sub>	Collector-Emitter Breakdown Voltage	$I_{C}$ =-10mA, $R_{BE}$ = $\infty$	-230			V
BV <sub>EBO</sub>	Emitter-Base Breakdown Voltage	ter-Base Breakdown Voltage I <sub>E</sub> =-5mA, I <sub>C</sub> =0				V
I <sub>CBO</sub>	Collector Cut-off Current	V <sub>CB</sub> =-230V, I <sub>E</sub> =0			-5.0	μΑ
I <sub>EBO</sub>	Emitter Cut-off Current	$V_{EB}$ =-5V, I <sub>C</sub> =0			-5.0	μA
h <sub>FE1</sub>	DC Current Gain	V <sub>CE</sub> =-5V, I <sub>C</sub> =-1A	55		160	
h <sub>FE2</sub>	DC Current Gain	V <sub>CE</sub> =-5V, I <sub>C</sub> =-7A	35	60		
V <sub>CE</sub> (sat)	Collector-Emitter Saturation Voltage	I <sub>C</sub> =-8A, I <sub>B</sub> =-0.8A		-0.4	-3.0	V
V <sub>BE</sub> (on)	Base-Emitter On Voltage	V <sub>CE</sub> =-5V, I <sub>C</sub> =-7A		-1.0	-1.5	V
f <sub>T</sub>	Current Gain Bandwidth Product	V <sub>CE</sub> =-5V, I <sub>C</sub> =-1A		30		MHz
C <sub>ob</sub>	Output Capacitance	V <sub>CB</sub> =-10V, f=1MHz		360		pF

\* Pulse Test: Pulse Widt=20  $\mu s,$  Duty Cycle≤2%

### **Ordering Information**

Part Number	Marking	Package	Packing Method	Remarks
FJP1943RTU	J1943R	TO-220	TUBE	hFE1 R grade
FJP1943OTU	J1943O	TO-220	TUBE	hFE1 O grade



### **Typical Characteristics**




Figure 7. Power Derating





Figure 8. Thermal Resistance





\* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. TO OBTAIN THE LATEST, MOST UP-TO-DATE DATASHEET AND PRODUCT INFORMATION, VISIT OUR WEBSITE AT <u>HTTP://WWW.FAIRCHILDSEMI.COM</u>, FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

#### AUTHORIZED USE

Unless otherwise specified in this data sheet, this product is a standard commercial product and is not intended for use in applications that require extraordinary levels of quality and reliability. This product may not be used in the following applications, unless specifically approved in writing by a Fairchild officer: (1) automotive or other transportation, (2) military/aerospace, (3) any safety critical application – including life critical medical equipment – where the failure of the Fairchild product reasonably would be expected to result in personal injury, death or property damage. Customer's use of this product is subject to agreement of this Authorized Use policy. In the event of an unauthorized use of Fairchild's product, Fairchild accepts no liability in the event of product failure. In other respects, this product shall be subject to Fairchild's Worldwide Terms and Conditions of Sale, unless a separate agreement has been signed by both Parties.

#### ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Terms of Use

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

#### PRODUCT STATUS DEFINITIONS

Definition of Terms			
Datasheet Identification	Product Status	Definition	
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.	
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.	
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.	
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.	

Rev. 177

## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Fairchild Semiconductor: <u>FJP1943RTU</u> <u>FJP1943OTU</u>