

3-Channel 25mA Linear LED Driver

Features

- ▶ ±6% current accuracy @ 4.0 -15V
- 90V standoff voltage
- Separate enable pins for each channel allow for PWM dimming
- Over-temperature protection
- 8-Lead SOIC (w/Heat Slug) package

Applications

- LCD backlighting
- Indicator lamps

General Description

The CL325 is designed to drive 3 strings of LEDs at a constant current of 25mA.


Other drivers with currents in the range of 20 - 30mA are available. The drive current is fixed, with a \pm 6% tolerance over a V_{OUT} range of 4 - 15V.

Separate enable pins for each channel allow for PWM dimming, 3-step linear dimming, or individual disconnection of faulty LED strings.

Over-temperature protection circuitry shuts down all 3 channels when the nominal die temperature reaches 135°C. Normal operation resumes when the die temperature drops by 30°C.

The CL325 is available in the 8-Lead SOIC (w/Heat Slug) package and requires a single ceramic bypass capacitor which may be shared among several drivers.

Block Diagram and Typical Application Circuit



Ordering Information

Device	8-Lead SOIC (w/Heat Slug) 4.90x3.90mm body 1.70mm height (max) 1.27mm pitch
CL325	CL325SG-G

-G indicates package is RoHS compliant ('Green')

Absolute Maximum Ratings


Parameter	Value
Supply voltage, V _{IN}	-0.5V to +100V
Output voltage, V _{OUT}	-0.5V to +100V
Enable voltage, $V_{_{EN}}$	-0.5V to +6.5V
Operating temperature ⁽¹⁾	-40°C
Storage temperature	-65°C to +150°C

Absolute Maximum Ratings are those values beyond which damage to the device may occur. Functional operation under these conditions is not implied. Continuous operation of the device at the absolute rating level may affect device reliability. All voltages are referenced to device ground.

Note:

1. Maximum junction temperature internally limited.

Pin Configuration



8-Lead SOIC (w/Heat Slug) (SG)

Product Marking

YYWW CL325 LLLL	YY = Year Sealed WW = Week Sealed L = Lot Number = "Green" Packaging									
8-Lead SOIC (w/Heat Slug) (SG)										

Sym Parameter Min Max Units Conditions Тур V Supply voltage 6.5 90 V ---- $\overline{EN} = 0$ V 15 $\rm V_{out}$ Output voltage 4.0 _ $\overline{EN} = 1$ 90 V 100 Enable toggling frequency 0 kHz f_{EN} _ ___ T_{\perp} Junction temperature -40 119 °C _ ___ 100 CIN V_{IN} capacitor _ nF ---

Recommended Operating Conditions (all voltages with respect to GND pin)


Thermal Characteristics

Sy	/m	Parameter	Min	Тур	Max	Units	Conditions
θ	JA	Thermal resistance, junction to ambient	-	48	-	°C/W	Mounted on JEDEC test PCB (2s 2p)
T	_IM	Over-temperature limit	120	135	150	°C	
T _H	IYS	Over-temperature hysteresis	-	30	-	°C	


Sym	Parameter	Min	Тур	Max	Units	Conditions
		-	220	250	μA	ĒN ₁₋₃ = 1
I _{IN}	V _{IN} supply current	-	2.2	2.3	mA	ĒN ₁₋₃ = 0
I _{OUT(OFF)}	Output current, off	-	4.0	10	μA	ĒN _x = 1
		-	-	26.5		$\overline{EN}_{x} = 0, V_{OUT} = 0 - 4.0V$
I _{OUT(ON)}	Output current, on	23.5	25.0	26.5	mA	ĒN _x = 0, V _{out} = 4.0 - 15V
		22.5	25.0	27.5		ĒN _x = 0, V _{out} = 15 - 90V
V _{EN(ON)}	Enable voltage, on	-	-	0.8	V	
V _{EN(OFF)}	Enable voltage, off	2.4	-	-	V	
C _{EN}	Enable input capacitance	-	5.0	10	pF	
I _{ENL}	Enable low input current	-	-	1.0	μA	V _{EN} = 0V
I _{ENH}	Enable high input current	-	-	1.0	μA	V _{EN} = 5.0V
t _{on}	Enable on delay	-	2.0	2.4	μs	
t _{RISE}	Output current rise time	-	1.0	1.2	μs	
t _{off}	Enable off delay	-	440	800	ns	
t _{FALL}	Output current fall time	-	170	250	ns	

Electrical Characteristics (Over recommended operating conditions. T_A @ 25°C unless otherwise specified.)


Timing




Temperature Effects




Load Regulation




Recommended PCB Layout



Higher LED Current




By paralleling outputs, higher LED currents can be achieved. In addition, linear dimming in 3 discrete steps may be obtained by enabling 1, 2, or 3 outputs.




Lowering CL325 Power Dissipation: Separate V_{IN} Supply

CL325 power dissipation may be lowered by supplying the CL325 from a voltage source (V_{IN}) that is lower in voltage than the LED supply (V_{II}).

Lowering CL325 Power Dissipation: Dropping Resistor




Lowering CL325 Power Dissipation: Zener Diode



Pin Description

Pin #	Name	Description
1	EN1	
2	EN2	Output enable, active low.
3	EN3	
4	GND	Circuit common.
5	OUT3	
6	OUT2	Constant current output (sinking). Connect the cathodes of the LEDs to these pins.
7	OUT1	
8	VIN	Supply voltage. 6.5V to 90V. Bypass locally with a 100nF capacitor to ground.
Underside Plate	GND	The exposed underside plate is internally connected to the GND pin. The plate may either be left floating or connected to ground. Solder the plate to an exposed copper area on the PCB for heatsinking purposes (see recommended layout).

8-Lead SOIC (Narrow Body w/Heat Slug) Package Outline (SG) 4.90x3.90mm body, 1.70mm height (max), 1.27mm pitch



Notes:

1. A Pin 1 identifier must be located in the index area indicated. The Pin 1 identifier can be: a molded mark/identifier; an embedded metal marker; or a printed indicator.

Symbo	bl	Α	A1	A2	b	D	D1	E	E1	E2	е	h	L	L1	L2	θ	θ1
Dimension (mm)	MIN	1.25*	0.00	1.25	0.31	4.80*	3.30 [†]	5.80*	3.80*	2.29†	4 07	0.25	0.40			0 0	5 °
	NOM	-	-	-	-	4.90	-	6.00	3.90	-	1.27 BSC	-	-	1.04 REF	0.25 BSC	-	-
	MAX	1.70	0.15	1.55*	0.51	5.00*	3.81 [†]	6.20*	4.00*	2.79 [†]	200	0.50	1.27		Bee	8 0	15 ⁰

JEDEC Registration MS-012, Variation BA, Issue E, Sept. 2005.

* This dimension is not specified in the original JEDEC drawing. The value listed is for reference only.

† This dimension is a non-JEDEC dimension.

Drawings not to scale.

Supertex Doc. #: DSPD-8SOSG, Version C090408.

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information go to <u>http://www.supertex.com/packaging.html</u>.)

Supertex inc. does not recommend the use of its products in life support applications, and will not knowingly sell them for use in such applications unless it receives an adequate "product liability indemnification insurance agreement." Supertex inc. does not assume responsibility for use of devices described, and limits its liability to the replacement of the devices determined defective due to workmanship. No responsibility is assumed for possible omissions and inaccuracies. Circuitry and specifications are subject to change without notice. For the latest product specifications refer to the Supertex inc. website: http://www.supertex.com.

©2008 Supertex inc. All rights reserved. Unauthorized use or reproduction is prohibited.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Microchip: CL325SG-G