

Single high-voltage switching diode Rev. 2 — 5 November 2010

Product data sheet

1. **Product profile**

1.1 General description

Single high-voltage switching diode, fabricated in planar technology, and encapsulated in a SOD523 (SC-79) ultra small Surface-Mounted Device (SMD) plastic package.

1.2 Features and benefits

■ High switching speed: $t_{rr} \le 50$ ns

High reverse voltage: V_R ≤ 300 V

Repetitive peak forward current: I_{FRM} ≤ 1 A

Ultra small SMD plastic package

AEC-Q101 qualified

1.3 Applications

- High-speed switching
- High-voltage switching

1.4 Quick reference data

Table 1. Quick reference data

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
I _F	forward current	$T_{sp} \leq 90~^{\circ}C$	<u>[1]</u> -	-	250	mA
V_R	reverse voltage		-	-	300	V
t _{rr}	reverse recovery time		[2] _	16	50	ns

^[1] T_{sp} is the solder point temperature at the soldering point of the cathode tab.



^[2] When switched from I_F = 30 mA to I_R = 30 mA; R_L = 100 Ω ; measured at I_R = 3 mA.

Single high-voltage switching diode

2. Pinning information

Table 2. Pinning

Pin	Description		Simplified outline	Graphic symbol
1	cathode	<u>[1]</u>		
2	anode		1 2	1 2 006aab040

^[1] The marking bar indicates the cathode.

3. Ordering information

Table 3. Ordering information

Type number	Package		
	Name	Description	Version
BAS521	SC-79	plastic surface-mounted package; 2 leads	SOD523

4. Marking

Table 4. Marking codes

Type number	Marking code
BAS521	L4

5. Limiting values

Table 5. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134).

Symbol	Parameter	Conditions	Min	Max	Unit
V_R	reverse voltage		-	300	V
V_{RRM}	repetitive peak reverse voltage		-	300	V
I _F	forward current	$T_{sp} \le 90 ^{\circ}C$	<u>[1]</u>	250	mA
I _{FRM}	repetitive peak forward current	t_p = 1 ms; δ = 0.25	-	1	Α
I _{FSM}	non-repetitive peak forward current	square wave; t _p = 1 μs	[2] _	4.5	Α
P _{tot}	total power dissipation	$T_{sp} \le 90 ^{\circ}C$	[1][3]	500	mW
Tj	junction temperature		-	150	°C
T _{amb}	ambient temperature		-65	+150	°C
T_{stg}	storage temperature		-65	+150	°C

^[1] T_{sp} is the solder point temperature at the soldering point of the cathode tab.

^[2] $T_j = 25$ °C prior to surge.

^[3] Reflow soldering is the only recommended soldering method.

Single high-voltage switching diode

6. Thermal characteristics

Table 6. Thermal characteristics

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
$R_{th(j-a)}$	thermal resistance from junction to ambient	in free air	[1][2]	-	500	K/W
$R_{th(j-sp)}$	thermal resistance from junction to solder point		[3] _	-	120	K/W

- [1] Device mounted on an FR4 PCB, single-sided copper, tin-plated and standard footprint.
- [2] Reflow soldering is the only recommended soldering method.
- [3] Soldering point of cathode tab.

7. Characteristics

Table 7. Characteristics


 T_{amb} = 25 °C unless otherwise specified.

Symbol	Parameter	Conditions		Min	Тур	Max	Unit
V_{BR}	breakdown voltage	$I_R = 100 \mu A$		300	340	-	V
V _F	forward voltage	I _F = 100 mA	<u>[1]</u>	-	0.95	1.1	V
I _R	reverse current	V _R = 250 V		-	30	150	nA
		V _R = 250 V; T _{amb} = 150 °C		-	40	100	μΑ
C _d	diode capacitance	$f = 1 MHz; V_R = 0 V$		-	0.4	5	pF
t _{rr}	reverse recovery time		[2]	-	16	50	ns

^[1] Pulse test: t_p = 300 μ s; δ = 0.02.

^[2] When switched from I_F = 30 mA to I_R = 30 mA; R_L = 100 $\Omega;$ measured at I_R = 3 mA.

Single high-voltage switching diode



- (1) $T_{amb} = 150 \, ^{\circ}C$
- (2) $T_{amb} = 75 \, ^{\circ}C$
- (3) $T_{amb} = 25 \, ^{\circ}C$

Fig 1. Forward current as a function of forward voltage; typical values






Fig 3. Forward current as a function of ambient temperature; derating curve



 $V_R = V_{Rmax}$


Fig 2. Reverse current as a function of junction temperature; typical values




 $f = 1 \text{ MHz}; T_{amb} = 25 \text{ }^{\circ}\text{C}$

Fig 4. Diode capacitance as a function of reverse voltage; typical values

Single high-voltage switching diode



8. Test information




8.1 Quality information

This product has been qualified in accordance with the Automotive Electronics Council (AEC) standard *Q101 - Stress test qualification for discrete semiconductors*, and is suitable for use in automotive applications.

Single high-voltage switching diode

9. Package outline



10. Packing information

Table 8. Packing methods


The indicated -xxx are the last three digits of the 12NC ordering code.[1]

Type number	Package	e Description Packing		g quantity		
			3000	8000	10000	
BAS521 SOD523		2 mm pitch, 8 mm tape and reel	-	-315	-	
		4 mm pitch, 8 mm tape and reel	-115	-	-	
			-	-	-135	

^[1] For further information and the availability of packing methods, see Section 14.

Single high-voltage switching diode

11. Soldering



Single high-voltage switching diode

12. Revision history

Table 9. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes
BAS521 v.2	20101105	Product data sheet	-	BAS521_1
Modifications:	 Section 8 "Te Figure 7: sup Section 10 "F Section 11 "S 	Features and benefits": amendest information": added perseded by minimized package Packing information": added Soldering": added Legal information": updated		
BAS521_1	20030812	Product data sheet	-	-

Single high-voltage switching diode

13. Legal information

13.1 Data sheet status

Document status[1][2]	Product status[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

- [1] Please consult the most recently issued document before initiating or completing a design.
- [2] The term 'short data sheet' is explained in section "Definitions"
- [3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.nxp.com.

13.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

13.3 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or

malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors accepts no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nxp.com/profile/terms, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from national authorities.

BAS521

All information provided in this document is subject to legal disclaimers.

© NXP B.V. 2010. All rights reserved.

Single high-voltage switching diode

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

13.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

14. Contact information

For more information, please visit: http://www.nxp.com

For sales office addresses, please send an email to: salesaddresses@nxp.com

BAS521 NXP Semiconductors

Single high-voltage switching diode

15. Contents

1	Product profile
1.1	General description 1
1.2	Features and benefits1
1.3	Applications 1
1.4	Quick reference data 1
2	Pinning information 2
3	Ordering information 2
4	Marking 2
5	Limiting values 2
6	Thermal characteristics 3
7	Characteristics 3
8	Test information 5
8.1	Quality information 5
9	Package outline 6
10	Packing information 6
11	Soldering 7
12	Revision history 8
13	Legal information 9
13.1	Data sheet status 9
13.2	Definitions 9
13.3	Disclaimers
13.4	Trademarks10
14	Contact information 10
15	Contents 11

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

NXP:

BAS521,115 BAS521,135 BAS521,315