

Ultra low capacitance bidirectional double ESD protection array

Rev. 01 — 14 August 2008

Product data sheet

1. Product profile

1.1 General description

Ultra low capacitance bidirectional double ElectroStatic Discharge (ESD) protection diode array in a SOT883 (SC-101) leadless ultra small Surface-Mounted Device (SMD) plastic package designed to protect up to two signal lines from the damage caused by ESD and other transients.

1.2 Features

Bidirectional ESD protection of up to two lines
 Ultra low diode capacitance: C_d = 2.9 pF
 IEC 61000-4-2; level 4 (ESD)
 Ultra low leakage current: I_{RM} = 5 nA
 AEC-Q101 qualified

1.3 Applications

- Computers and peripherals
 Audio and video equipment
 Cellular handsets and accessories
 10/100/1000 Mbit/s Ethernet
- Communication systems
- Portable electronics
- Subscriber Identity Module (SIM) card protection
- FireWire
- High-speed data lines

1.4 Quick reference data

Table 1.Quick reference data

```
T_{amb} = 25 \circ C unless otherwise specified.
```

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
Per diode)					
V _{RWM}	reverse standoff voltage		-	-	5	V
C _d	diode capacitance	$f = 1 \text{ MHz}; V_R = 0 \text{ V}$	-	2.9	3.5	pF



Ultra low capacitance bidirectional double ESD protection array

2. Pinning information

Table 2.	Pinning		
Pin	Description	Simplified outline	Graphic symbol
1	cathode (diode 1)		
2	cathode (diode 2)		
3	common cathode	2 Transparent top view	2

3. Ordering information

Table 3. Ordering information						
Type number	Package					
	Name	Description	Version			
PESD5V0U2BM	SC-101	leadless ultra small plastic package; 3 solder lands; body $1.0 \times 0.6 \times 0.5$ mm	SOT883			

4. Marking

Table 4.	Marking codes	
Type num	ber	Marking code
PESD5V0	U2BM	GA

5. Limiting values

Table 5. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134).

Symbol	Parameter	Conditions	Min	Max	Unit
Per device					
Tj	junction temperature		-	150	°C
T _{amb}	ambient temperature		-55	+150	°C
T _{stg}	storage temperature		-65	+150	°C

PESD5V0U2BM_1

Ultra low capacitance bidirectional double ESD protection array

Table 6.ESD maximum ratings

 $T_{amb} = 25 \circ C$ unless otherwise specified.


Symbol	Parameter	Conditions		Min	Max	Unit
Per diode)					
V _{ESD} electrostatic discharge voltage			[1][2]			
	IEC 61000-4-2 (contact discharge)		-	10	kV	
		MIL-STD-883 (human body model)		-	8	kV

[1] Device stressed with ten non-repetitive ESD pulses.

[2] Measured from pin 1 or 3 to pin 2 or 3.

Table 7. ESD standards compliance

Standard	Conditions
Per diode	
IEC 61000-4-2; level 4 (ESD)	> 15 kV (air); > 8 kV (contact)
MIL-STD-883; class 3 (human body model)	> 4 kV




Ultra low capacitance bidirectional double ESD protection array

6. Characteristics

 $T_{amb} = 25 \circ C$ unless otherwise specified.


Symbol	Parameter	Conditions	Min	Тур	Max	Unit
Per diod	le					
V _{RWM}	reverse standoff voltage		-	-	5	V
I _{RM}	reverse leakage current	$V_{RWM} = 5 V$	-	5	100	nA
V_{BR}	breakdown voltage	$I_R = 5 \text{ mA}$	5.5	6.5	9.5	V
C _d	diode capacitance	f = 1 MHz				
		$V_R = 0 V$	-	2.9	3.5	pF
		$V_R = 5 V$	-	1.9	-	pF
r _{dif}	differential resistance	I _R = 1 mA	-	-	100	Ω



NXP Semiconductors

PESD5V0U2BM

Ultra low capacitance bidirectional double ESD protection array




PESD5V0U2BM_1

Ultra low capacitance bidirectional double ESD protection array

7. Application information

The PESD5V0U2BM is designed for the protection of up to two bidirectional data or signal lines from the damage caused by ESD and surge pulses. The device may be used on lines where the signal polarities are both, positive and negative with respect to ground.



Circuit board layout and protection device placement

Circuit board layout is critical for the suppression of ESD, Electrical Fast Transient (EFT) and surge transients. The following guidelines are recommended:

- 1. Place the PESD5V0U2BM as close to the input terminal or connector as possible.
- 2. The path length between the PESD5V0U2BM and the protected line should be minimized.
- 3. Keep parallel signal paths to a minimum.
- 4. Avoid running protected conductors in parallel with unprotected conductors.
- Minimize all Printed-Circuit Board (PCB) conductive loops including power and ground loops.
- 6. Minimize the length of the transient return path to ground.
- 7. Avoid using shared transient return paths to a common ground point.
- 8. Ground planes should be used whenever possible. For multilayer PCBs, use ground vias.

8. Test information


8.1 Quality information

This product has been qualified in accordance with the Automotive Electronics Council (AEC) standard *Q101* - *Stress test qualification for discrete semiconductors*, and is suitable for use in automotive applications.

PESD5V0U2BM 1

Ultra low capacitance bidirectional double ESD protection array

9. Package outline



10. Packing information

Table 9. Packing methods

The indicated -xxx are the last three digits of the 12NC ordering code.[1]


Type number	Package	Description	Packing quantity 10000
PESD5V0U2BM	SOT883	2 mm pitch, 8 mm tape and reel	-315

[1] For further information and the availability of packing methods, see <u>Section 14</u>.

PESD5V0U2BM_1

Ultra low capacitance bidirectional double ESD protection array

11. Soldering



Ultra low capacitance bidirectional double ESD protection array

12. Revision history

Table 10. Revision hist	Revision history							
Document ID	Release date	Data sheet status	Change notice	Supersedes				
PESD5V0U2BM_1	20080814	Product data sheet	-	-				

13. Legal information

13.1 Data sheet status

Document status ^{[1][2]}	Product status ^[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.nxp.com.

13.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

13.3 Disclaimers

General — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in medical, military, aircraft, space or life support equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors accepts no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk. **Applications** — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) may cause permanent damage to the device. Limiting values are stress ratings only and operation of the device at these or any other conditions above those given in the Characteristics sections of this document is not implied. Exposure to limiting values for extended periods may affect device reliability.

Terms and conditions of sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nxp.com/profile/terms, including those pertaining to warranty, intellectual property rights infringement and limitation of liability, unless explicitly otherwise agreed to in writing by NXP Semiconductors. In case of any inconsistency or conflict between information in this document and such terms and conditions, the latter will prevail.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

ESD protection devices — These products are only intended for protection against ElectroStatic Discharge (ESD) pulses and are not intended for any other usage including, without limitation, voltage regulation applications. NXP Semiconductors accepts no liability for use in such applications and therefore such use is at the customer's own risk.

13.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

14. Contact information

For more information, please visit: http://www.nxp.com

For sales office addresses, please send an email to: salesaddresses@nxp.com

PESD5V0U2BM_1
Product data sheet

NXP Semiconductors

PESD5V0U2BM

Ultra low capacitance bidirectional double ESD protection array

15. Contents

1	Product profile 1
1.1	General description
1.2	Features
1.3	Applications 1
1.4	Quick reference data
2	Pinning information 2
3	Ordering information 2
4	Marking 2
5	Limiting values 2
6	Characteristics 4
7	Application information 6
8	Test information 6
8.1	Quality information 6
9	Package outline 7
10	Packing information
11	Soldering 8
12	Revision history 9
13	Legal information 10
13.1	Data sheet status 10
13.2	Definitions 10
13.3	Disclaimers
13.4	Trademarks 10
14	Contact information 10
15	Contents 11

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© NXP B.V. 2008.

All rights reserved.



founded by

For more information, please visit: http://www.nxp.com For sales office addresses, please send an email to: salesaddresses@nxp.com

Date of release: 14 August 2008 Document identifier: PESD5V0U2BM_1

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

NXP: PESD5V0U2BM,315